

Sounds Heavenly

Powered Line Cables for Beolink Passive / MCL2P

Thank you for purchasing a Sounds Heavenly Powered Line Cable for your Bang and Olufsen Beolink Passive/MCL2P Link Room amplifier.

This high-quality cable assembly contains an Input Cable (blue), a Splitter Cable (black) and also a precision switch-mode power supply which generates the trigger signals required to allow you to connect a Bang and Olufsen Beolink Passive or Beolink MCL2P amplifier directly to a non-B&O music source (via a headphone output or a variable line level RCA output). This cable is suitable for home or professional use and is designed to be left permanently connected to the amplifier and speakers in dry, indoor conditions only. It can be used in any country with an alternating current (AC) mains supply between 110 and 240 volts.

Fitting Instructions:-

1. Locate the black Splitter cable. This will have an 8 pin male DIN plug fitted. Connect this plug to the socket on your Beolink amplifier marked "Powerlink" or "Powerlink Input".
2. If you are using this cable with a Beolink Passive, please ensure that the Masterlink cable and IR cable are not connected.
3. Locate the blue signal cable and connect this to either a headphone output (minijack) or RCA/phono output (only use audio pre-out sockets which are variable level, ie. volume controlled). The 5 pin DIN plug on this cable connects to one of the two sockets on the black Splitter cable.
4. Locate the power supply and connect the 7 pin DIN plug to the other socket on the black Splitter cable. Turn on the power to your audio system and Beolink amplifier.
5. When the cable power supply is connected, the Beolink amplifier will turn on and this will stay on until the cable power supply is disconnected.
6. Sit back and enjoy the music!

Important note: Under no circumstances should these cables be connected to fixed level Tape Out or Line Out sockets, or to Audio Out sockets on a TV or DVD player, as these are set at full volume - this can result in serious and expensive damage to the equipment (and probably your ears!)

* Beolink is a trademark of Bang and Olufsen. This powered cable set is compatible with Beolink products having a Powerlink input mode as indicated above.